


ASNT8050-PQB

7.4-8.8GHz and 10.8-12.7GHz Programmable PLL with integrated VCOs

- Programmable clock multiplier (CMU) with two selectable frequency ranges of internal PLL
- Optional operational mode as a clock divider with PLL disabled
- Closed-Loop SSB phase noise at 10MHz offset better than 98dB/Hz
- Selectable internal divider ratio of 8 or 16
- On-chip Loss-of-Lock control circuit
- External RC loop filter
- LVDS or CML input reference clock interface
- Full-rate CML clock input and output interfaces
- LVDS divided clock output with optional 90°-step phase adjustment
- Exhibits low jitter and limited temperature variation over industrial temperature range
- Single +3.3V power supply
- Power consumption: 630mW
- Fabricated in SiGe for high performance, yield, and reliability
- Standard MLF/QFN 40-pin package





DESCRIPTION




Fig. 1. Functional Block Diagram

ASNT8050-PQB is a clock multiplication unit (CMU) with a dual-range phase-locked loop (PLL) incorporating high-speed voltage-controlled oscillators (VCOs). The part features several control functions shown in Table 1. All functions are further described in the specified sections.

Table 1. PLL Control Functions

| Control signal | Logic State | | | Described in |
|----------------|----------------------------|-------------------------|---------------------------|--------------|
| | "0" | Not connected (default) | "1" | |
| off12g | Higher VCO range | Same as "0" state | Lower VCO range | PLL |
| offcho | HS COB enabled | Same as "0" state | HS COB disabled | HS COB |
| phs1/phs2 | See Table 4 | | | CPR |
| off16b | Clock division ratio of 16 | Same as "0" state | Clock division ratio of 8 | PLL, CPR |
| offpll | PLL enabled | Same as "0" state | PLL disabled | PLL |
| oncm1 | LVDS input interface | Same as "0" state | CML input interface | LS CIB |

One of the two frequency ranges can be selected by the control signal **off12g**. In the main operational mode, the IC shown in Fig. 1 accepts a low-speed reference clock **cr16p/cr16n** with the frequency $f/8$ or $f/16$ and converts it into a high-speed output clock **cho** with the frequency f and the low-speed output clock **clo** with the corresponding frequency $f/8$ or $f/16$. The frequency of the reference and output clocks is defined by the settings of the control signal **off16b**.

The high-speed clock output buffer can be enabled/disabled by the control signal **offcho**. One of four 90° shifted phases of the low-speed output clock with the frequency $f/16$ can be selected by control signals **phs1** and **phs2**. This phase selection is not available for the output clock with the frequency $f/8$.

When operating in the closed-loop mode, the PLL requires an external loop filter connected to pins **ftr1** and **ftr2**. The output signal **lol** indicates the locked or unlocked state of the PLL. The PLL also supports an open-loop mode of operation with its selected VCO controlled externally by voltages applied to the filter pins **ftr1** and **ftr2**.



The chip can operate as a divider of the input high-speed clock **cep/cen** if the PLL is disabled by the control signal **offpll**. The division ratio of 8 or 16 can be selected by the control signal **off16b**.

The IC uses a single +3.3V power supply and is characterized for operation from -25°C to 125°C of junction temperature.

HS CIB

The High-Speed Clock Input Buffer (HS CIB) can process an external clock signal **cep/cen** with frequencies from DC to the specified maximum value. The clock inputs support the CML logic interface with on chip *50Ohm* termination to **vcc** and may be used differentially, AC/DC coupled, single-ended, or in any combination. In the DC-coupling mode, the input signal's common mode voltage should comply with the specifications shown in ELECTRICAL CHARACTERISTICS. In the AC-coupling mode, the input termination provides the required common mode voltage automatically. The differential DC signaling mode is recommended for optimal performance.

LS CIB

The Low-Speed Clock Input Buffer (LS CIB) is a proprietary universal input buffer (UIB) that can run at a high frequency. The UIB's input termination impedance is controlled by the CMOS signal **oncm1** and is set to *100Ohm* differential if **oncm1="0"** (true LVDS mode, default state) or *50Ohm* single-ended to **vcc** if **oncm1="1"** (CML mode). Possible input clock application schemes are detailed in Table 2, where **Vcm** is the common-mode voltage of the input clock signal.

Table 2. LS Input Clock Application Schemes

| Interface type | Clock type | cr16p signal | | | cr16n signal | | |
|------------------------------|------------|--------------|---------------|--------------|--------------|---------------|-------------|
| | | Swing, mV | Connection | Vcm, V | Swing, mV | Connection | Vcm, V |
| LVDS (oncm1="0") | Diff. | 70-to-500 | DC | 1.2±1.0 | 70-to-500 | DC | 1.2±1.0 |
| | SE | 140-to-900 | AC | - | Threshold | DC | vee-to-vcc |
| | | Threshold | DC | vee-to-vcc | 140-to-900 | AC | - |
| CML (oncm1="1") | Diff. | 70-to-500 | DC | vcc -Swing/2 | 70-to-500 | DC | vcc-Swing/2 |
| | | | AC | - | | AC | - |
| | SE | 140-to-900 | AC | - | - | Not connected | - |
| | | | AC | - | Threshold | DC | vcc |
| | | - | Not connected | - | 140-to-900 | AC | - |
| | | Threshold | DC | vcc | 140-to-900 | AC | - |

As can be seen, the UIB is designed to accept differential signals with DC common mode voltages between the negative (**vee**) and the positive (**vcc**) supply rails, as well as AC common mode noise with a frequency up to *5MHz* and voltage levels from **vee** to **vee+2.4V**. It can also receive single-ended signals with a threshold voltage between **vee** and **vcc** applied to the unused pin of the differential input interface.

PLL

The PLL contains a phase frequency detector, a charge pump, an on-chip integrator with an additional off-chip filter connected between pins **ftr1** and **ftr2**, and two selectable LC-tank VCOs with different central frequencies. The recommended parameters of the external filter schematic components shown in Fig. 2 are for reference only and can be modified based on specific requirements.




Fig. 2. Recommended External Filter Schematic

The PLL is activated by the external control signal `offpll="0"`. In case of `offpll="1"` (default state), the PLL is disabled and the chip operates as a divider by 8 or 16. The division ratio is defined by the CMOS control signal `off16b` (division by 8 if `off16b="1"`; division by 16 if `off16b="0"`, default state).

The main function of the PLL is to synthesize the full-rate clock `C` by aligning the phase and frequency of the divided clock from the internal divider to the externally applied reference clock `cr16`. Selection of the required VCO is defined by the CMOS control signal `off12g` (lower-speed VCO if `off12g="1"`; higher-speed VCO if `off12g="0"`, default state). The frequency of the required reference clock is defined by the CMOS control signal `off16b` (divided-by-8 if `off16b="1"`; divided-by-16 if `off16b="0"`, default state). The state of the PLL is indicated by the output CMOS loss-of-lock alarm signal `lol` (`lol="1"` if PLL is not locked, `lol="0"` if phases and frequencies of internal and reference clocks are matching).

If required, the selected VCO can be externally controlled by voltages applied to the pins `ftr1` and `ftr2` as shown in Table 3. In this case, the PLL is operating in the open-loop mode. The unused VCO is completely disabled to save power.

Table 3. VCO External Control Modes

| ftr1 signal, V | ftr2 signal, V | VCO frequency |
|----------------|----------------|---------------|
| Vccm+0.8=3.1 | Vccm=2.3 | min |
| Vccm-0.8=1.5 | Vccm=2.3 | max |
| Vccm=2.3 | Vccm+0.8=3.1 | max |
| Vccm=2.3 | Vccm-0.8=1.5 | min |

Divider-by-16

The Divider-by-16 (/16) includes 4 divide-by-2 circuits connected in series. The clocks divided by 8 and 16 are supplied to the PLL's phase detector and to the clock processor CPR.

CPR

The clock processor (CPR) receives divided clocks from the divider and supplies the selected clock to the low-speed clock output buffer. The type of the clock is defined by the CMOS control signal `off16b` (divided-by-8 if `off16b="1"`; divided-by-16 if `off16b="0"`, default state). The phase of the divided-by-16 clock `C16` can be altered utilizing the CMOS control pins `phs1` and `phs2` as shown in Table 4.

Table 4. Output Clock Phase Selection

| phs1 | phs2 | C16 phase |
|---------------|---------------|-----------|
| vee (default) | vee (default) | 0° |
| vee | vcc | 90° |
| vcc | vee | 180° |
| vcc | vcc | 270° |



HS COB

The High Speed Clock Output Buffer (HS COB) receives the high-speed clock from the PLL and converts it into the CML output signal **cho**. The buffer can be enabled or disabled by the external CMOS control signal **offcho** (disabled if **offcho**="1"; enabled if **offcho**="0", default state).

LS COB

The LVDS Low-Speed Clock Output Buffer (LS COB) converts the signal from the CPR into the LVDS output signal **clo**. The proprietary low-power LVDS output buffer utilizes a special architecture that ensures operation at frequencies up to 2.0GHz with a low power consumption level of 30mW. The buffer satisfies all requirements of the IEEE Std. 1596.3-1996 and ANSI/TIA/EIA-644-1995. For the correct operation, it requires external differential 100Ohm DC termination at the receiver side. These pins should **NEVER be CONNECTED** to devices with 50Ohm termination to ground **WITHOUT DC BLOCKS!**

ABSOLUTE MAXIMUM RATINGS

Caution: Exceeding the absolute maximum ratings shown in Table 5 may cause damage to this product and/or lead to reduced reliability. Functional performance is specified over the recommended operating conditions for power supply and temperature only. AC and DC device characteristics at or beyond the absolute maximum ratings are not assumed or implied. All min and max voltage limits are referenced to ground (assumed **vee**).

Table 5. Absolute Maximum Ratings

| Parameter | Min | Max | Units |
|-----------------------------|-----|------|-------|
| Supply Voltage (VCC) | | 3.6 | V |
| Power Consumption | | 0.7 | W |
| RF Input Voltage Swing (SE) | | 1.0 | V |
| Case Temperature | | +90 | °C |
| Storage Temperature | -40 | +100 | °C |
| Operational Humidity | 10 | 98 | % |
| Storage Humidity | 10 | 98 | % |



TERMINAL FUNCTIONS

| TERMINAL | | | DESCRIPTION |
|--|-------------------------------|--|--|
| Name | No. | Type | |
| High-Speed I/Os | | | |
| cep | 14 | CML input | CML differential external clock inputs with internal SE 50 Ω termination to VCC |
| cen | 13 | | |
| chop | 17 | CML output | CML differential clock outputs with internal SE 50 Ω termination to VCC. Require external SE 50 Ω termination to VCC |
| chon | 16 | | |
| Low-Speed I/Os | | | |
| cr16p | 1 | Input | LVDS/CML clock inputs. See LS CIB for allowed application schemes |
| cr16n | 2 | | |
| clop | 20 | Output | LVDS clock outputs. See LS COB for a detailed description |
| clon | 19 | | |
| Controls | | | |
| off16b | 4 | Input | 3.3V CMOS control signals |
| offcho | 5 | | |
| off12g | 9 | | |
| offpll | 11 | | |
| oncml | 21 | | |
| phs2 | 24 | | |
| phs1 | 25 | | |
| ftr1 | 7 | Input | Pins for connecting the external loop filter. Can be also used for VCO external control in the open-loop mode |
| ftr2 | 8 | | |
| lol | 6 | Output | 3.3V CMOS control output |
| Supply and Termination Voltages | | | |
| Name | Description | Pin Number | |
| vcc | Positive power supply (+3.3V) | 12, 15, 18, 27, 28, 29, 31, 32, 33, 34, 35, 36, 37, 38, 39 | |
| vee | Negative power supply (0V) | 3, 10, 22, 23, 26, 30, 40 | |



ELECTRICAL CHARACTERISTICS

| PARAMETER | MIN | TYP | MAX | UNIT | COMMENTS |
|---|----------|----------|------|------|---|
| General Parameters | | | | | |
| vee | | 0.0 | | V | External ground |
| vcc | 3.1 | 3.3 | 3.5 | V | ±6% |
| Ivcc | 185 | | 195 | mA | |
| Power consumption | | 630 | | mW | |
| Junction temperature | -40 | 25 | 125 | °C | |
| HS Input Clock (cep/cen) | | | | | |
| Frequency | DC | | 14 | GHz | |
| Swing | 220 | | 800 | mV | Differential or SE, p-p, at 14GHz |
| | 50 | | 800 | mV | Differential or SE, p-p, at 4GHz |
| CM Voltage Level | vcc-0.8 | | vcc | V | Must match for both inputs |
| Duty Cycle | 40% | 50% | 60% | | |
| LS Input Clock (cr16p/cr16n) | | | | | |
| Frequency | DC | | 1600 | MHz | |
| Swing | 140 | | 900 | mV | Differential or SE, p-p |
| CM Voltage Level | vee | 1.6 | vcc | V | Must match for both inputs |
| HS Output Clock (chop/chon) | | | | | |
| Frequency | DC | | 14 | GHz | |
| Logic "1" level | | vcc | | V | |
| Logic "0" level | | vcc-0.85 | | V | |
| Jitter | | 6 | | ps | Peak-to-peak at 12.5GHz |
| Duty Cycle | | 50% | | | |
| LS Output Clock (clon/clon) | | | | | |
| Frequency | DC | | 1750 | MHz | |
| Interface | | LVDS | | | Meets the IEEE Std. |
| CMOS control inputs and outputs (off16b, offcho, off12g, offpll, oncm1, phs1, phs2, lol) | | | | | |
| Logic "1" level | vcc-0.3 | | | V | |
| Logic "0" level | | vee+0.3 | | V | |
| VCOs | | | | | |
| Low frequency of VCO 1 | | 10.8 | | GHz | Higher-speed VCO. Active if off12g = "0" |
| High frequency of VCO 1 | | 12.7 | | GHz | |
| Low frequency of VCO 2 | | 7.4 | | GHz | Lower-speed VCO. Active if off12g = "1" |
| High frequency of VCO 2 | | 8.8 | | GHz | |
| External control common mode vccm | | 2.3 | | V | In the open-loop mode |
| External control voltage range | vccm-0.8 | vccm+0.8 | | V | In the open-loop mode |

PACKAGE INFORMATION

The chip die is housed in a standard 40-pin QFN package shown in Fig. 3. It is recommended that the center heat slug located on the back side of the package is soldered to the **vee** plain that is ground for the positive supply.

The part's identification label is ASNT8050-PQB. The first 8 characters of the name before the dash identify the bare die including general circuit family, fabrication technology, specific circuit type, and part version while the 3 characters after the dash represent the package's manufacturer, type, and pin out count.

This device complies with the Restriction of Hazardous Substances (RoHS) per 2011/65/EU for all ten substances.




Fig. 3. QFN 40-Pin Package Drawing (All Dimensions in mm)



REVISION HISTORY

| Revision | Date | Changes |
|----------|---------|---|
| 1.7.2 | 02-2020 | Updated Package Information |
| 1.6.2 | 07-2019 | Updated Letterhead |
| 1.6.1 | 08-2015 | Correct Fig. 2 External Filter Schematic |
| 1.5.1 | 08-2014 | Corrected format Corrected default state of the <code>offpll</code> input |
| 1.4.1 | 05-2013 | Corrected clock names in Table 2 |
| 1.3.1 | 03-2013 | Corrected name of the supply in the Absolute Maximum Ratings table Removed broken link |
| 1.2.1 | 03-2013 | Revised title Revised description Revised absolute maximum ratings Revised terminal functions Revised electrical characteristics Revised package information Updated format |
| 1.1 | 05-2012 | Corrected supply information |
| 1.0 | 04-2012 | First release |